

Congratulation for purchasing the high quality Vape ignition kit for your Lambretta! Wiring it up is dead easy and very similar to all other electronic ignitions for the Lambretta.

Setting it up using an AC regulator

YELLOW wire gives the AC current that goes to the regulator.

BLACK wire from stator plate is earth wire. Connecting it to the regulator makes sense, but can go to all other good earth points.

RED wire goes from the stator to the CDI.

BLUE wire from the CDI is connected to the green wire from the ignition or kill switch.

BROWN wire is connected to earth.*

BLACK wire from CDI is connected to earth.*

**ATTENTION: a good and solid connection of the CDI to earth is essential on the VAPE ignition, otherwise the CDI might be damaged!*

